



Managing illness on mylife CamAPS FX

Note: Please discuss all recommendations with your diabetes team.

Most illnesses will generally increase glucose levels:

- Consider using the “Boost” mode if you notice glucose levels are running higher than usual when unwell.
 - Stress, emotions and pain can also cause glucose levels to rise.
 - The “Boost” mode can be programmed to run for up to 13 hours at a time. You will be able to see when “Boost” mode was programmed if you turn the smartphone in landscape position (to view the detailed graph), in the PDF report or in Glooko®.
 - The “Boost” mode makes the algorithm deliver about 35 % more insulin if you are running high but it will stop “boosting” when it predicts glucose levels will reach your personal target.
 - It is recommended that you monitor glucose levels more closely when unwell.
- Please check for blood ketones if glucose levels are constantly high.
 - It may also be worth checking for ketones, even when glucose levels are not raised, if you have been vomiting and/or having diarrhoea.
- Consider changing the infusion set and the insulin reservoir if glucose remains high despite mylife CamAPS FX working hard to deliver insulin to correct glucose levels.

Ketone management:

- If you have ketones above 1.5 mmol/L in adults or above 0.6 mmol/L in children, please consider stopping Auto mode and following the ketone management guidelines your diabetes team have given you. This may include:
 - Giving a correction via an insulin syringe or pen,
 - Changing the infusion set and reservoir and
 - Setting an increased temporary basal rate on the pump.
 - Drinking plenty of sugar-free fluid as well as eating small amounts of carbohydrate will also help to clear the ketones.
- Please contact your diabetes team if you need clinical support or advice.
- Auto mode can be restarted once the ketones are no longer present (less than 0.6 mmol/L).


Stopping and starting Auto mode:

- Slide the toggle in the bottom right corner of the mylife CamAPS FX home screen to the left to stop Auto mode.
- When Auto mode is stopped:
 - The mylife YpsoPump's pre-programmed basal rate will automatically start running.
 - You can still use mylife CamAPS FX's bolus calculator to deliver insulin boluses for meals and snacks.
 - Manual corrections can be delivered via the mylife CamAPS FX bolus calculator as well.
- To restart Auto mode, slide the toggle in the bottom of the home screen to the right to switch mylife CamAPS FX back on.

Note: Please discuss all recommendations with your diabetes team.



Auto mode activated



Auto mode deactivated

rtCGM: real time continuous glucose monitoring

mylife YpsoPump and CamAPS FX are class IIb devices. Only rapid-acting insulin at a concentration of 100 U/ml (insulin analogue) may be used with the mylife YpsoPump system. Always read the label and use only as directed. Consult your healthcare professional to see if these products are right for you.

Disclaimer:

The product images are for illustrative purposes only. // mylife and YpsoPump are registered trademarks of Ypsomed AG. // CamAPS is a registered trademark of CamDiab Ltd. // The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc., and any use of such marks by Ypsomed is under license. // Other trademarks and trade names are those of their respective owners.

 For safety information on mentioned products, see Instructions for Use.